

THE POSSIBILITIES ARE INFINITE



## LifeBook U1010

- World's Smallest Tablet-convertible UMPC
- Intelligently designed to suit your working style. Interact with LifeBook U1010 like a Notebook, Tablet PC or Hand-held
- Versatile with convertible form factor and pen input capability
- Optimal internet connectivity via built-in Wireless LAN, LAN and Bluetooth®
- Designed for Genuine Windows Vista™ operating system

Specifications	
Platform	Intel® Ultra Mobile platform 2007 - Intel® processor A110 (800MHz, 512KB L2 cache, 400MHz FSB) - Intel® 945GU Express Chipset - Intel® ICH7U I/O Controller Hub
Operating System	Genuine Windows Vista™ Home Premium
Display	5.6-inch SuperFine WSVGA, 1024 X 600 pixels, Passive Touch Panel
Memory	1GB DDR2 400MHz
Hard Disk	40GB
Bluetooth®	v2.0
Battery	Up to 3hrs¹ (2-cell Li-Ion 2600mAh)
Weight	Approx. 0.61kg
Detailed Specifications	
Hard Disk Drive	1.8-inch PATA Ultra DMA 100 (4200rpm), S.M.A.R.T. support
Graphics	Integrated Intel® Graphics with 3D Accelerator
High Definition (HD) Audio	RealTek ALC262 HD audio codec with built-in digital microphone
Communication	Bluetooth® v2.0, RealTek 8101L 100Base Ethernet, Super AG™/ Super G™³ wireless connection with dual antenna and Integrated Camera 0.3 Mega Pixel
User Interface	Keyboard with Glide Point: 56-key, 14mm key pitch, 1.3mm key stroke Fingerprint Sensor with vertical scroll functions
Card Slot	1 x Type I/II CF Card slot 1 x Secure Digital (SD) Card Reader
Connector Interface	USB 2.0 x 1, VGA (external display) and RJ45 (LAN) via LAN/ VGA adapter connector, Audio-in, Audio-out, Power Adapter DC-in
Quick Launch Panel	Two programmable application buttons, two programmable up/down key buttons, one rotation button, one Ctrl+Alt+Del button and one FnKey button
Security⁴	User and supervisor BIOS password, Boot Sector Write Prevention, Fingerprint Sensor, Trusted Platform Module (TPM)
Dimensions	171mm (W) x 133mm (D) x 26.5-32.0mm (H)
Bundled Accessories	
AC Adapter	Input AC100-240V, Output DC16V 40W
Bundled Software	Microsoft Origami Experience Pack, Acronis True Image, Softex OmniPass, Adobe Acrobat Reader, Sun Microsystems Java Runtime, Fujitsu UpdateNavi⁵, Fujitsu Hardware Diagnostic, Fujitsu Display Manager
Software on CD	1 year Full Licensed Norman Virus Control
VGA/ LAN Adapter²	External cable for connection to RJ45 (LAN), VGA (external display)
Carrying Case²	Portable slip case
Optional Accessories	
Port Replicator	Connector Interface: USB 2.0 x 4, VGA (external display), RJ45 (LAN), Power Adapter DC-in
Extended Battery	4-cell Li-Ion 5200mAh 7.2V



Maximize your media experience.



The above information shows the general technical specifications of the product and does not represent actual configuration. For specific configurations and their availability, please check with your local distributors.

1. Results obtained from BAPCO MobileMark2002 performed on systems with maximum battery life settings. Actual battery life will vary based on screen brightness, sound volume settings, running applications, connected peripherals, power management settings, battery conditioning, and other customer preferences. Built-in bay device or hard drive usage may also have a significant impact on battery life.
2. Please check actual bundling with country local distributor.
3. Super AG™ and Super G™ are trademarks of Atheros® Communications. Super AG™ and Super G™ modes deliver up to 108 Mbps raw data rate with typical end user throughput exceeding 60Mbps in a wireless network environment where wirelessly connected equipment are using Atheros Super AG™ or Super G™ enabled chipsets.
4. BIOS Lock needs a supervisor/user password to access BIOS setup. BIOS settings can be configured to prompt for password at every first bootup or all bootup sequences. Access to BIOS setup is needed to configure Hard Disk Lock. Hard Disk Lock requires an access key to retrieve data on the hard disk. This is a Data Confidentiality security feature. LifeBook Lock requires a supervisor/ user password to bootup the LifeBook when it powers up or resumes last session from suspend/hibernate mode. This is an anti-theft feature with more than 800,000 password combinations using the buttons on the Quick Launch Panel. Anti-theft Lock Slot allows the use of a lock to physically secure the LifeBook. Smartcard slot usage is dependent on customer's solution. Fingerprint sensor uses AuthenTec TruePrint™ Technology and Softex OmniPass to remember customer list of user IDs and passwords. Full security unlock sequence - LifeBook Lock, Bootup Lock (BIOS Lock), Hard Disk Lock, Fingerprint Windows Logon.  
NOTE: Loss of password requires the LifeBook to be returned to Japan factory for system refresh. Cost of shipment and lost data will be borne by the customer. Backup your user's profile before changing HDD. Without the user's profile associated with a document at the point of encryption, Softex OmniPass cannot decrypt the encrypted document.
5. UpdateNavi is a Fujitsu Proprietary application that updates LifeBook drivers by connecting automatically to Fujitsu's server. This will help update your LifeBook with the latest software drivers and utilities to ensure compatibility between hardware and software, maintaining smooth operation anytime, anywhere.

It is natural for all thin-film transistor (TFT) liquid crystal displays (LCD) to show a small number of missing or discolored dots. These are commonly known as non-conforming pixels. This is a technology limitation of TFT LCD and does not represent a defect. Fujitsu warranty does not cover limitations in technology such as non-conforming pixels.

Specifications reflected above are engineering and hardware specifications. They do not represent actual usage or operating dimensions, sizes, performances and weights as these are dependent on factors such as operating temperature, type of operating system and application used, connected devices and accessories as well as hardware configurations of the notebook. Please check the compatibility of 3rd party accessories before purchase.

## www.pc-ap.fujitsu.com

**AUSTRALIA & NEW ZEALAND:**  
**Fujitsu PC Australia**  
Toll Free: (AU) 1800 288 283  
(NZ) 0800 288 283  
Fax : (61-2) 9889 3360  
**www.lifebook.com.au**

**CHINA:**  
**Fujitsu PC China Division**  
Tel : (86-21) 3310 0808  
Fax : (86-21) 3310 0606  
**cn.fujitsu.com/pc**

**HONG KONG:**  
**Fujitsu PC Asia Pacific Ltd**  
Tel : (852) 3101 8133  
Fax : (852) 3101 0633

**INDIA:**  
**Fujitsu India Limited**  
Tel : (91-11) 2370 6070  
Fax : (91-11) 2370 6079

**INDONESIA:**  
**Fujitsu Indonesia**  
Tel : (62-21) 570 9330  
Fax : (62-21) 573 5150

**MALAYSIA:**  
**Fujitsu PC Asia Pacific Pte Ltd**  
Tel : (60-3) 2093 3997  
Fax : (60-3) 2093 4245

**PHILIPPINES:**  
**Fujitsu Philippines Inc.**  
Tel : (63-2) 812 4001  
Fax : (63-2) 817 7576

**SINGAPORE:**  
**Fujitsu PC Asia Pacific Pte Ltd**  
Tel : (65) 6776 0688  
Fax : (65) 6776 0788

**THAILAND:**  
**Fujitsu Systems Business (Thailand) Ltd PC Division**  
Tel : (66-2) 263 7888  
Fax : (66-2) 263 7880

**TAIWAN:**  
**Fujitsu Taiwan Ltd**  
Tel : (886-2) 2311 2255  
Fax : (886-2) 2311 2277

**VIETNAM:**  
**Fujitsu Vietnam Ltd**  
Tel : (84-4) 831 3895  
Fax : (84-4) 831 3898

Note: For countries not listed above, please contact our Singapore office.

All rights to the mentioned trademarks reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of Fujitsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.

JOB NO.: 1629 • Printed by Fujitsu PC Asia Pacific Limited in June 2007. Information is correct at time of printing.